



iTrans DX2-R-22



Dante 2CH Analog Output Dongle

All Rights Reserved

Version: iTrans DX2-R-22_2022V1.0

Product Introduction

Thanks for choosing the iTrans DX2-R-22. It connects to your Dante network and supports Analog 0X2 channels audio, allowing analog amplifier to your Dante audio network.


Features

- Plug and Play
- 24-bit audio support
- 0X2 audio channels
- Supports 802.3af PoE

Packing List

- 1x iTrans DX2-R-22
- 1x User Manual

Note: Please contact your distributor immediately if any damage or defect in the components is found



Panel Description

- ① **RJ45:** Dante network communication port. Green steady light indicates system ready; yellow flashing light indicates link/data traffic. The green light will flash to identify the device when clicking the Dante Controller "Identify" button (an eye-shaped computer symbol) on the host computer.
- ② **XLR:** 2 x XLR female, connect output device

Technical Specification

Audio	
Max signal level	+18 dBu/+4 dBu/0 dBu 0 dBV/-10 dBV
Frequency Response	20Hz to 20kHz(-/+0.5dB)
Impedance	150 Ohm balanced 75 Ohm unbalanced
Dynamic Range	>100 dB
Signal to Noise Ratio	>100 dB
THD	<0.01% @+4 dBu
Dante	
Sample Rate	44.1kHz, 48kHz, 96kHz
Bit Depth	24
Dante Device latency	1,2 or 5ms (configurable)

	using Dante Controller)
Model Name	Analog 0X2
General	
Operation Temperature	-5 to +55°C (+23° to +131°F)
Storage Temperature	-25 to +70°C (-13° to +158°F)
Power	802.3af PoE
Power Consumption	2.6W(Max)
Dimension (W*H*D)	30 x 28 x 114 mm
Cable length	300mm
Net Weight	145g

 infobit



WWW.INFOBITAV.COM

INFO@INFOBITAV.COM